



Product End-of-Life Disassembly Instructions

Product Category: Data Storage Devices

Marketing Name / Model

[List multiple models if applicable.]

HP StorageWorks RDX Removable Disk Backup System (internal) 160 Gb / AJ765A

HP StorageWorks RDX Removable Disk Backup system (internal) 320 Gb / AJ767A

Purpose: The document is intended for use by end-of-life recyclers or treatment facilities. It provides the basic instructions for the disassembly of HP products to remove components and materials requiring selective treatment, as defined by EU directive 2002/96/EC, Waste Electrical and Electronic Equipment (WEEE).

1.0 Items Requiring Selective Treatment

1.1 Items listed below are classified as requiring selective treatment.

1.2 Enter the quantity of items contained within the product which require selective treatment in the right column, as applicable.

Item Description	Notes	Quantity of items included in product
Printed Circuit Boards (PCB) or Printed Circuit Assemblies (PCA)	With a surface greater than 10 sq cm	1
Batteries	All types including standard alkaline and lithium coin or button style batteries	0
Mercury-containing components	For example, mercury in lamps, display backlights, scanner lamps, switches, batteries	0
Liquid Crystal Displays (LCD) with a surface greater than 100 sq cm	Includes background illuminated displays with gas discharge lamps	0
Cathode Ray Tubes (CRT)		0
Capacitors / condensers (Containing PCB/PCT)		0
Electrolytic Capacitors / Condensers measuring greater than 2.5 cm in diameter or height		0
External electrical cables and cords		2
Gas Discharge Lamps		0
Plastics containing Brominated Flame Retardants		0
Components and parts containing toner and ink, including liquids, semi-liquids (gel/paste) and toner	Include the cartridges, print heads, tubes, vent chambers, and service stations.	0
Components and waste containing asbestos		0
Components, parts and materials containing refractory ceramic fibers		0
Components, parts and materials containing radioactive substances		0

2.0 Tools Required

List the type and size of the tools that would typically be used to disassemble the product to a point where components and materials requiring selective treatment can be removed.

Tool Description	Tool Size (if applicable)
Phillips	#1
Phillips	#2
Torx	T6
Allen	2 mm

3.0 Product Disassembly Process

3.1 List the basic steps that should typically be followed to remove components and materials requiring selective treatment:

1. Peel up and remove rubber feet
2. Remove 7 bottom screws, 3 T6-Torx and 4 #2 phillips, and slide top cover off to rear
3. Remove rear M2 allen screw, unplug fan cable and remove bottom cover
4. Remove 2 M3 nuts from fan, pull off ground strip from bottom cover
5. Pry finger snaps out to remove bezel from base, eject rod falls out
6. Disconnect button board cable at main board, deflect snap fingers to remove button board and esd shield from base
7. Remove 3 T6-Torx screws from main board and remove board
8. Remove 3 T6-Torx gear retention screws to remove cam, gears and latch
- 9.

3.2 Optional Graphic. If the disassembly process is complex, insert a graphic illustration below to identify the items contained in the product that require selective treatment (with descriptions and arrows identifying locations).

