


# ArubaOS DRT 1.0\_47726



Release Notes

## Copyright Information

© 2014 Aruba Networks, Inc. Aruba Networks trademarks include  airwave, Aruba Networks®, Aruba Wireless Networks®, the registered Aruba the Mobile Edge Company logo, Aruba Mobility Management System®, Mobile Edge Architecture®, People Move. Networks Must Follow®, RFPProtect®, Green Island®. All rights reserved. All other trademarks are the property of their respective owners.

## Open Source Code

Certain Aruba products include Open Source software code developed by third parties, including software code subject to the GNU General Public License (GPL), GNU Lesser General Public License (LGPL), or other Open Source Licenses. Includes software from Litech Systems Design. The IF-MAP client library copyright 2011 Infoblox, Inc. All rights reserved. This product includes software developed by Lars Fenneberg et al. The Open Source code used can be found at this site

[http://www.arubanetworks.com/open\\_source](http://www.arubanetworks.com/open_source)

## Legal Notice

The use of Aruba Networks, Inc. switching platforms and software, by all individuals or corporations, to terminate other vendors' VPN client devices constitutes complete acceptance of liability by that individual or corporation for this action and indemnifies, in full, Aruba Networks, Inc. from any and all legal actions that might be taken against it with respect to infringement of copyright on behalf of those vendors.

## Warranty

This hardware product is protected by an Aruba warranty. For more information, refer to the ArubaCare service and support terms and conditions.

---

<b>Contents</b> .....	<b>3</b>
<b>Downloadable Regulatory Table</b> .....	<b>8</b>
<b>Overview</b> .....	<b>8</b>
<b>Contacting Support</b> .....	<b>8</b>
<b>Uploading and Activating the DRT</b> .....	<b>9</b>
Important Points to Remember .....	9
Copying the DRT .....	9
In the WebUI .....	9
In the CLI .....	9
Activating the DRT .....	10
In the WebUI .....	10
In the CLI .....	10
Related Show Commands .....	10
<b>Supported Countries</b> .....	<b>12</b>
Albania .....	15
Algeria .....	17
Argentina .....	18
Australia .....	20
Austria .....	22
Azerbaijan .....	24
Bahrain .....	25
Belarus .....	26
Belgium .....	27
Bermuda .....	29
Bolivia .....	30
Bosnia and Herzegovina .....	31
Botswana .....	33
Brazil .....	34
Bulgaria .....	36

---

Canada	38
Chile	40
China	42
Colombia	44
Costa Rica	46
Côte d'Ivoire	48
Croatia	49
Cyprus	51
Czech Republic	53
Denmark	55
Dominican Republic	57
Ecuador	59
Egypt	60
El Salvador	62
Estonia	63
Finland	65
France	67
Germany	69
Ghana	71
Greece	72
Guam	74
Guatemala	75
Hong Kong	76
Hungary	78
Iceland	80
India	82
Indonesia	84
Ireland	86
Israel	88
Italy	90
Jamaica	92
Japan	93
Jordan	95

---

Kazakhstan .....	96
Kenya .....	98
Kuwait .....	99
Laos .....	100
Latvia .....	101
Lebanon .....	103
Liechtenstein .....	104
Lithuania .....	106
Luxembourg .....	108
Macau .....	110
Macedonia .....	112
Malaysia .....	114
Mali .....	116
Malta .....	117
Maritime Offshore .....	119
Maritime .....	121
Mexico .....	123
Montenegro .....	125
Morocco .....	127
Namibia .....	128
Netherlands .....	129
New Zealand .....	131
Nicaragua .....	133
Niger .....	134
Nigeria .....	135
Norway .....	136
Oman .....	138
Pakistan .....	139
Panama .....	140
Papua New Guinea .....	141
Paraguay .....	142
Peru .....	143
Philippines .....	145

---

Poland .....	147
Puerto Rico .....	149
Qatar .....	151
Romania .....	153
Russia .....	155
Saudi Arabia .....	157
Senegal .....	159
Serbia .....	160
Singapore .....	161
Slovak Republic .....	163
Slovenia .....	165
South Africa .....	167
South Korea .....	169
Spain .....	171
Sri Lanka .....	173
Sweden .....	174
Switzerland .....	176
Taiwan .....	178
Thailand .....	180
Trinidad and Tobago .....	182
Tunisia .....	183
Turkey .....	184
Uganda .....	186
Ukraine .....	188
United Arab Emirates .....	190
United Kingdom .....	192
United States of America .....	194
Uruguay .....	196
Venezuela .....	197
Vietnam .....	198
Zambia .....	200
Zimbabwe .....	201

---

<b>DRT Versions</b> .....	<b>202</b>
1.0_47726 .....	203
1.0_47726 .....	204
1.0_47156 .....	207
1.0_46705 .....	209
1.0_46413 .....	210
1.0_46245 .....	211
1.0_45530 .....	213
1.0_45134 .....	214
1.0_44265 .....	217

The Downloadable Regulatory Table (DRT) features allow new regulatory approvals to be distributed without waiting for a new software patch and upgrade. The file containing AP Regulatory-Cert information will be released periodically on the customer support site. The Downloadable Regulatory Table file can then be uploaded to an Aruba controller and communicated to deployed APs.




---

Use of the Downloadable Regulatory Table feature requires ArubaOS 6.4.1 or newer.

---

## Overview

[Uploading and Activating the DRT on page 9](#) explains how to upload and activate the Regulatory-Cert.

## Contacting Support

**Table 1:** *Contact Information*

Main Site	<a href="http://arubanetworks.com">arubanetworks.com</a>
Support Site	<a href="http://support.arubanetworks.com">support.arubanetworks.com</a>
Airheads Social Forums and Knowledge Base	<a href="http://community.arubanetworks.com">community.arubanetworks.com</a>
North American Telephone	1-800-943-4526 (Toll Free) 1-408-754-1200
International Telephone	<a href="http://www.arubanetworks.com/support-services/support-program/contact-support/">http://www.arubanetworks.com/support-services/support-program/contact-support/</a>
Software Licensing Site	<a href="https://licensing.arubanetworks.com/">https://licensing.arubanetworks.com/</a>
End of Support Information	<a href="http://www.arubanetworks.com/support-services/end-of-life-products/end-of-life-policy/">http://www.arubanetworks.com/support-services/end-of-life-products/end-of-life-policy/</a>
Wireless Security Incident Response Team (WSIRT)	<a href="http://www.arubanetworks.com/support-services/security-bulletins/">http://www.arubanetworks.com/support-services/security-bulletins/</a>
<b>Support Email Addresses</b>	
Americas and APAC	<a href="mailto:support@arubanetworks.com">support@arubanetworks.com</a>
EMEA	<a href="mailto:emea_support@arubanetworks.com">emea_support@arubanetworks.com</a>
Wireless Security Incident Response Team (WSIRT)	<a href="mailto:wsirt@arubanetworks.com">wsirt@arubanetworks.com</a>



# Uploading and Activating the DRT

The following section describes the process for uploading and activating the Downloadable Regulatory Table.

## Important Points to Remember

- When the DRT file is activated, the new file is checked against the default file built into ArubaOS. If the file is of a newer version, the activation is allowed. If the file is of a lower version, then the activation is not completed. The controller's CLI displays the following message upon failure:

```
(host) #ap regulatory activate reg-data-1.0_00002.dat
Failed to activate regulatory file reg-data-1.0_00002.dat. File Version should be greater than 1.0_43859
```

- APs do not rebootstrap or reboot on activation.
- If there is change in channel list or power level, APs will change the channel/power level. Impact is same as that of ARM channel/power change in that case.
- Clients are not disconnected upon regulatory file activation. Max latency impact during activation (with no channel changes) are less than 1s. (applies to power change too)
- With channel change, the impact is similar to ARM channel change (depends on client behavior and if CSA is enabled or not)
- If support for the AP (Country) is added, the AP will move from AM to AP mode (if the AP is configured in AP mode of operation)

## Copying the DRT

You can use the following protocols to copy the DRT to a controller:

- FTP
- TFTP
- SCP

Additionally, regulatory files saved to a USB drive can be uploaded to a controller equipped with a USB port.

You can copy the DRT to the controller using the WebUI or CLI.

### In the WebUI

1. Navigate to the **Maintenance > File > Copy Files** page.
2. Select the source (TFTP, FTP, SCP, or USB) where the file exists.
3. The controller WebUI will automatically select **Flash File System** under the **Destination Selection** menu.
4. Click **Apply**.

### In the CLI

Use one of the following **copy** commands to download the DRT file to the controller:

```
copy
  scp: <scphost> <username> <filename> flash: <destfilename>
  tftp: <tftphost> <filename> flash: <destfilename>
  usb: partition <partition-number> <filename> flash: <destfilename>
```

To view the current regulatory and the content of the file, use the following commands:

```
show ap regulatory
show ap allowed-channels country-code <country-code> ap-type <ap-type>
show ap allowed-max-eirp ap-name <ap-name> country-code <country-code>
show ap debug received-reg-table ap-name <ap-name>
```

## Activating the DRT

Once the DRT file has been added to the controller, the new regulatory information must be activated and pushed to the APs.

### In the WebUI

To activate a specific regulatory file using the WebUI:

1. Navigate to **Maintenance > File > Regulatory Files**.
2. Select a DRT file from the **File List**.
3. Click **Activate**.

### In the CLI

To activate a specific DRT file loaded on the controller, use the following command:

```
ap regulatory activate <filename>
```

To return to the factory default regulatory-cert, use the following command:

```
ap regulatory reset
```

In a master-local-standby deployment, the file syncing profile can be enabled to ensure that the Regulatory-cert stored on the master is shared with its subordinate controllers. File syncing is enabled by default, with a default sync time of 30 minutes. The sync time can be set between 30 to 180 minutes, To configure the file syncing profile, use the following commands:

```
(host) (config) #file syncing profile
(host) (File syncing profile) #file-syncing-enable
(host) (File syncing profile) #sync-time 30
```

## Related Show Commands

To view the current regulatory version on all controllers, execute the following command:

```
show switches regulatory
show file syncing profile
```



This section contains a list of all countries and APs that are currently supported in this release of the Downloadable Regulatory Table.

- [Albania](#)
- [Argentina](#)
- [Australia](#)
- [Austria](#)
- [Azerbaijan](#)
- [Bahrain](#)
- [Belarus](#)
- [Belgium](#)
- [Bermuda](#)
- [Bolivia](#)
- [Bosnia and Herzegovina](#)
- [Brazil](#)
- [Bulgaria](#)
- [Canada](#)
- [Chile](#)
- [China](#)
- [Colombia](#)
- [Costa Rica](#)
- [Croatia](#)
- [Cyprus](#)
- [Czech Republic](#)
- [Denmark](#)
- [Dominican Republic](#)
- [Ecuador](#)
- [Egypt](#)
- [El Salvador](#)
- [Estonia](#)
- [Finland](#)
- [France](#)
- [Germany](#)
- [Ghana](#)
- [Greece](#)
- [Guam](#)
- [Guatemala](#)
- [Hong Kong](#)
- [Hungary](#)

- [Iceland](#)
- [India](#)
- [Indonesia](#)
- [Ireland](#)
- [Israel](#)
- [Italy](#)
- [Japan](#)
- [Jordan](#)
- [Kazakhstan](#)
- [Kenya](#)
- [Kuwait](#)
- [Laos](#)
- [Latvia](#)
- [Lebanon](#)
- [Liechtenstein](#)
- [Lithuania](#)
- [Luxembourg](#)
- [Macau](#)
- [Macedonia](#)
- [Malaysia](#)
- [Mali](#)
- [Malta](#)
- [Maritime Offshore](#)
- [Maritime](#)
- [Mexico](#)
- [Montenegro](#)
- [Morocco](#)
- [Netherlands](#)
- [New Zealand](#)
- [Nicaragua](#)
- [Niger](#)
- [Nigeria](#)
- [Norway](#)
- [Oman](#)
- [Pakistan](#)
- [Panama](#)
- [Papua New Guinea](#)
- [Paraguay](#)
- [Peru](#)
- [Philippines](#)
- [Poland](#)
- [Puerto Rico](#)

- [Qatar](#)
- [Romania](#)
- [Russia](#)
- [Saudi Arabia](#)
- [Senegal](#)
- [Serbia](#)
- [Singapore](#)
- [Slovak Republic](#)
- [Slovenia](#)
- [South Africa](#)
- [South Korea](#)
- [Spain](#)
- [Sweden](#)
- [Switzerland](#)
- [Taiwan](#)
- [Thailand](#)
- [Trinidad and Tobago](#)
- [Tunisia](#)
- [Turkey](#)
- [Uganda](#)
- [Ukraine](#)
- [United Arab Emirates](#)
- [United Kingdom](#)
- [United States of America](#)
- [Uruguay](#)
- [Venezuela](#)
- [Vietnam](#)
- [Zambia](#)

## Albania

The following APs are currently supported in the Albania regulatory domain.

**Table 2: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	None

**Table 3: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 3: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1



## Algeria

The following APs are currently supported in the Algeria regulatory domain.

**Table 4: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132

**Table 5: Supported APs**

Device	Minimum Software Requirement
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-205	DRT 1.0_47726
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1

## Argentina

The following APs are currently supported in the Argentina regulatory domain.

**Table 6: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	52-64 100-112 149-161
802.11a (DFS)	None

**Table 7: Supported APs**

Device	Minimum Software Requirement
AP-103	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_46245

**Table 7: Supported APs**

Device	Minimum Software Requirement
AP-205	DRT 1.0_46245
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Australia

The following APs are currently supported in the Australia regulatory domain.

**Table 8: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	100-104 108-112 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	100-112 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 9: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 9: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-214	DRT 1.0_47156
AP-215	DRT 1.0_47156
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Austria

The following APs are currently supported in the Austria regulatory domain.

**Table 10: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 11: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 11: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Azerbaijan

The following APs are currently supported in the Azerbaijan regulatory domain.

**Table 12: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 13: Supported APs**

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1



## Bahrain

The following APs are currently supported in the Bahrain regulatory domain.

**Table 14:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 149-161
802.11a 80MHz (outdoor)	149-161
802.11a (DFS)	52 56 60 64

**Table 15:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-225	DRT 1.0_46245
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1

## Belarus

The following APs are currently supported in the Belarus regulatory domain.

**Table 16:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 17:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1

## Belgium

The following APs are currently supported in the Belgium regulatory domain.

**Table 18:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 19:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 19: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Bermuda

The following APs are currently supported in the Bermuda regulatory domain.

**Table 20:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 21:** *Supported APs*

Device	Minimum Software Requirement
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1

## Bolivia

The following APs are currently supported in the Bolivia regulatory domain.

**Table 22:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 23:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-135	DRT 1.0_47156
AP-225	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1

## Bosnia and Herzegovina

The following APs are currently supported in the Bosnia and Herzegovina regulatory domain.

**Table 24:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 25:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 25: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1



## Botswana

The following APs are currently supported in the Botswana regulatory domain.

**Table 26:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 27:** *Supported APs*

Device	Minimum Software Requirement
AP-135	DRT 1.0_47469
AP-225	ArubaOS 6.4.1

## Brazil

The following APs are currently supported in the Brazil regulatory domain.

**Table 28:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 29:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 29: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175	DRT 1.0_47726
AP-175P	DRT 1.0_47726
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	DRT 1.0_47726
AP-93	DRT 1.0_47726
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	DRT 1.0_47469
RAP-155P	DRT 1.0_47469
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Bulgaria

The following APs are currently supported in the Bulgaria regulatory domain.

**Table 30:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 31:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 31: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Canada

The following APs are currently supported in the Canada regulatory domain.

**Table 32:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 33:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 33: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	<ul style="list-style-type: none"><li>● Non DFS: ArubaOS 6.4.1</li><li>● DFS: DRT 1.0_46245</li></ul>
AP-205	<ul style="list-style-type: none"><li>● Non DFS: ArubaOS 6.4.1</li><li>● DFS: DRT 1.0_46245</li></ul>
AP-214	<ul style="list-style-type: none"><li>● Non DFS: DRT 1.0_45134</li><li>● DFS: DRT 1.0_47156</li></ul>
AP-215	<ul style="list-style-type: none"><li>● Non DFS: DRT 1.0_45134</li><li>● DFS: DRT 1.0_47156</li></ul>
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Chile

The following APs are currently supported in the Chile regulatory domain.

**Table 34:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	149-161
802.11a (DFS)	100 104 108 112 116 120 124 128 132 136 140

**Table 35:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_46245
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-124abg	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-125abg	ArubaOS 6.4.1



**Table 35: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245
AP-274	DRT 1.0_44265
AP-275	DRT 1.0_44265
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## China

The following APs are currently supported in the China regulatory domain.

**Table 36:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 149-161
802.11a 80MHz (outdoor)	149-161
802.11a (DFS)	52 56 60 64

**Table 37:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 37: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245
AP-274	ArubaOS 6.4.1
AP-275	DRT 1.0_45134
AP-68	ArubaOS 6.4.1
AP-68P	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-3WN	DRT 1.0_47156
RAP-3WNP	ArubaOS 6.4.1

## Colombia

The following APs are currently supported in the Colombia regulatory domain.

**Table 38:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	52-64 100-112 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 39:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 39: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	<ul style="list-style-type: none"><li>• Non-DFS: ArubaOS 6.4.1</li><li>• DFS: DRT 1.0_45134</li></ul>
AP-225	<ul style="list-style-type: none"><li>• Non-DFS: ArubaOS 6.4.1</li><li>• DFS: DRT 1.0_45134</li></ul>
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Costa Rica

The following APs are currently supported in the Costa Rica regulatory domain.

**Table 40:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	52-64 100-112 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 41:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-114	DRT 1.0_47156
AP-115	DRT 1.0_47156
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-204	DRT 1.0_47156
AP-205	DRT 1.0_47156
AP-224	DRT 1.0_47156
AP-225	DRT 1.0_47156
AP-274	DRT 1.0_47156

**Table 41: Supported APs**

Device	Minimum Software Requirement
AP-275	DRT 1.0_47156
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
RAP-108	DRT 1.0_47156
RAP-109	DRT 1.0_47156
RAP-3WN	DRT 1.0_47156
RAP-3WNP	DRT 1.0_47156

## Côte d'Ivoire

The following APs are currently supported in the Côte d'Ivoire regulatory domain.

**Table 42:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136

**Table 43:** *Supported APs*

Device	Minimum Software Requirement
AP-135	DRT 1.0_47469
AP-225	DRT 1.0_47469



## Croatia

The following APs are currently supported in the Croatia regulatory domain.

**Table 44:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 45:** *Supported APs*

Device	Minimum Software Requirement
AP-103H	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 45: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Cyprus

The following APs are currently supported in the Cyprus regulatory domain.

**Table 46:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 47:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 47: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Czech Republic

The following APs are currently supported in the Czech Republic regulatory domain.

**Table 48:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 49:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 49: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Denmark

The following APs are currently supported in the Denmark regulatory domain.

**Table 50:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 51:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 51: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1



## Dominican Republic

The following APs are currently supported in the Dominican Republic regulatory domain.

**Table 52:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	52-64 100-112 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 53:** *Supported APs*

Device	Minimum Software Requirement
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1

**Table 53: Supported APs**

Device	Minimum Software Requirement
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	<ul style="list-style-type: none"><li>• Non-DFS: ArubaOS 6.4.1</li><li>• DFS: DRT 1.0_45134</li></ul>
AP-225	<ul style="list-style-type: none"><li>• Non-DFS: ArubaOS 6.4.1</li><li>• DFS: DRT 1.0_45134</li></ul>
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Ecuador

The following APs are currently supported in the Ecuador regulatory domain.

**Table 54:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	52-64 100-112 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 55:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1

## Egypt

The following APs are currently supported in the Egypt regulatory domain.

**Table 56:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 149-161
802.11a 80MHz (outdoor)	149-161
802.11a (DFS)	52 56 60 64

**Table 57:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_46245
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 57: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## El Salvador

The following APs are currently supported in the El Salvador regulatory domain.

**Table 58:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 59:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1

## Estonia

The following APs are currently supported in the Estonia regulatory domain.

**Table 60:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 61:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 61: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1



## Finland

The following APs are currently supported in the Finland regulatory domain.

**Table 62:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 63:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 63: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## France

The following APs are currently supported in the France regulatory domain.

**Table 64:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 65:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 65: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Germany

The following APs are currently supported in the Germany regulatory domain.

**Table 66:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 67:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 67: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Ghana

The following APs are currently supported in the Ghana regulatory domain.

**Table 68:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 69:** *Supported APs*

Device	Minimum Software Requirement
AP-125	ArubaOS 6.4.1

## Greece

The following APs are currently supported in the Greece regulatory domain.

**Table 70: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 71: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1



**Table 71: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Guam

The following APs are currently supported in the Guam regulatory domain.

**Table 72:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	52-64 100-112 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 73:** *Supported APs*

Device	Minimum Software Requirement
AP-124	ArubaOS 6.4.1

## Guatemala

The following APs are currently supported in the Guatemala regulatory domain.

**Table 74:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 75:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1

## Hong Kong

The following APs are currently supported in the Hong Kong regulatory domain.

**Table 76: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 77: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_46245
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	<ul style="list-style-type: none"> <li>ArubaOS 6.4.1</li> <li>Channel 141-165: DRT 1.0_45134</li> </ul>
AP-121	<ul style="list-style-type: none"> <li>ArubaOS 6.4.1</li> <li>Channel 141-165: DRT 1.0_45134</li> </ul>

**Table 77: Supported APs**

Device	Minimum Software Requirement
AP-124	<ul style="list-style-type: none"><li>ArubaOS 6.4.1</li><li>Channel 141-165: DRT 1.0_45134</li></ul>
AP-125	<ul style="list-style-type: none"><li>ArubaOS 6.4.1</li><li>Channel 141-165: DRT 1.0_45134</li></ul>
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245
AP-224	DRT 1.0_44265
AP-225	DRT 1.0_44265
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Hungary

The following APs are currently supported in the Hungary regulatory domain.

**Table 78:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 79:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 79: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Iceland

The following APs are currently supported in the Iceland regulatory domain.

**Table 80:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 81:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1



**Table 81: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## India

The following APs are currently supported in the India regulatory domain.

**Table 82:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 149-161
802.11a 80MHz (outdoor)	149-161
802.11a (DFS)	None

**Table 83:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 83: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	DRT 1.0_45134
AP-275	DRT 1.0_45134
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Indonesia

The following APs are currently supported in the Indonesia regulatory domain.

**Table 84:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	149 153 157 161
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	149-161
802.11a 80MHz (outdoor)	149-161
802.11a (DFS)	None

**Table 85:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_46705
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1 HT40 mode not available
AP-114	ArubaOS 6.4.1
AP-115	DRT 1.0_46245
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1 HT40 mode not available
AP-175P	DRT 1.0_46245

**Table 85: Supported APs**

Device	Minimum Software Requirement
AP-204	DRT 1.0_46705
AP-215	DRT 1.0_47469
AP-224	ArubaOS 6.4.1
AP-225	DRT 1.0_46245
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	DRT 1.0_46245
RAP-109	DRT 1.0_46245
RAP-155	DRT 1.0_46245
RAP-155P	DRT 1.0_46245
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Ireland

The following APs are currently supported in the Ireland regulatory domain.

**Table 86:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 87:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 87: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Israel

The following APs are currently supported in the Israel regulatory domain.

**Table 88:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	None
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	None
802.11a 80MHz (indoor)	36-48 52-64
802.11a 80MHz (outdoor)	None
802.11a (DFS)	36 40 44 48 52 56 60 64

**Table 89:** *Supported APs*

Device	Minimum Software Requirement
AP-103	DRT 1.0_46245
AP-104	DRT 1.0_46245
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1



**Table 89: Supported APs**

Device	Minimum Software Requirement
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Italy

The following APs are currently supported in the Italy regulatory domain.

**Table 90:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 91:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 91: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Jamaica

The following APs are currently supported in the Jamaica regulatory domain.

**Table 92:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	149-161
802.11a 80MHz (outdoor)	149-161

**Table 93:** *Supported APs*

Device	Minimum Software Requirement
AP-225	DRT 1.0_47726

## Japan

The following APs are currently supported in the Japan regulatory domain.

**Table 94:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 95:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 95: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-214	DRT 1.0_47156
AP-215	DRT 1.0_47156
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	DRT 1.0_46413
AP-275	DRT 1.0_46413
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Jordan

The following APs are currently supported in the Jordan regulatory domain.

**Table 96:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 149-153 157-161
802.11a 80MHz (indoor)	36-48 149-161
802.11a 80MHz (outdoor)	36-48 149-161
802.11a (DFS)	None

**Table 97:** *Supported APs*

Device	Minimum Software Requirement
AP-103	DRT 1.0_47469
AP-104	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Kazakhstan

The following APs are currently supported in the Kazakhstan regulatory domain.

**Table 98:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128 149-161
802.11a (DFS)	None

**Table 99:** *Supported APs*

Device	Minimum Software Requirement
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1



**Table 99:** *Supported APs*

Device	Minimum Software Requirement
RAP-108	DRT 1.0_47469
RAP-109	DRT 1.0_47469
RAP-155	DRT 1.0_47469
RAP-155P	DRT 1.0_47469

## Kenya

The following APs are currently supported in the Kenya regulatory domain.

**Table 100:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140 149 153
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136 149-153
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 101:** *Supported APs*

Device	Minimum Software Requirement
AP-115	DRT 1.0_47469
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-205	DRT 1.0_47469
AP-215	DRT 1.0_47469
AP-225	DRT 1.0_47469
AP-275	DRT 1.0_47469

## Kuwait

The following APs are currently supported in the Kuwait regulatory domain.

**Table 102:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64
802.11g (outdoor)	None
802.11a (outdoor)	None
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64
802.11g 40MHz (outdoor)	None
802.11a 40MHz (outdoor)	None
802.11a 80MHz (indoor)	36-48 52-64
802.11a 80MHz (outdoor)	None
802.11a (DFS)	36 40 44 48 52 56 60 64

**Table 103:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-225	DRT 1.0_47156
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1

## Laos

The following APs are currently supported in the Laos regulatory domain.

**Table 104:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128 149-161
802.11a (DFS)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165

**Table 105:** *Supported APs*

Device	Minimum Software Requirement
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Latvia

The following APs are currently supported in the Latvia regulatory domain.

**Table 106:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 107:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1

**Table 107: Supported APs**

Device	Minimum Software Requirement
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Lebanon

The following APs are currently supported in the Lebanon regulatory domain.

**Table 108:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 149-161
802.11a 80MHz (outdoor)	36-48 52-64 149-161

**Table 109:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-225	DRT 1.0_47156
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1

## Liechtenstein

The following APs are currently supported in the Liechtenstein regulatory domain.

**Table 110:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 111:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1



**Table 111: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Lithuania

The following APs are currently supported in the Lithuania regulatory domain.

**Table 112: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 113: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45134
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 113: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Luxembourg

The following APs are currently supported in the Luxembourg regulatory domain.

**Table 114:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 115:** *Supported APs*

Device	Regulatory-Cert Version
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 115: Supported APs**

Device	Regulatory-Cert Version
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Macau

The following APs are currently supported in the Macau regulatory domain.

**Table 116:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	149-161
802.11a 80MHz (outdoor)	149-161

**Table 117:** *Supported APs*

Device	Minimum Software Requirement
AP-103	DRT 1.0_47469
AP-103H	DRT 1.0_47469
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1

**Table 117: Supported APs**

Device	Minimum Software Requirement
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Macedonia

The following APs are currently supported in the Macedonia regulatory domain.

**Table 118: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 119: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1



**Table 119: Supported APs**

Device	Minimum Software Requirement
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-224	ArubaOS 6.4.1
AP-225	DRT 1.0_47077
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Malaysia

The following APs are currently supported in the Malaysia regulatory domain.

**Table 120:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 149-161
802.11a 80MHz (outdoor)	36-48 52-64 149-161

**Table 121:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_46705
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1

**Table 121: Supported APs**

Device	Minimum Software Requirement
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-214	DRT 1.0_47726
AP-215	DRT 1.0_47469
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Mali

The following APs are currently supported in the Mali regulatory domain.

**Table 122:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 123:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1

## Malta

The following APs are currently supported in the Malta regulatory domain.

**Table 124:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 125:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 125: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Maritime Offshore

The following APs are currently supported in the Maritime Offshore regulatory domain.

**Table 126:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 132-144 149-161
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128 132-144 149-161

**Table 127:** *Supported APs*

Device	Minimum Software Requirement
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1

**Table 127: Supported APs**

Device	Minimum Software Requirement
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1



## Maritime

The following APs are currently supported in the Maritime regulatory domain.

**Table 128:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 132-144 149-161
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128 132-144 149-161

**Table 129:** *Supported APs*

Device	Minimum Software Requirement
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1

**Table 129:** *Supported APs*

Device	Minimum Software Requirement
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Mexico

The following APs are currently supported in the Mexico regulatory domain.

**Table 130:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	36-40 52-64 100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 131:** *Supported APs*

Device	Minimum Software Requirement
AP-103	DRT 1.0_47156
AP-103H	DRT 1.0_46413
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1

**Table 131: Supported APs**

Device	Minimum Software Requirement
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-215	DRT 1.0_46705
AP-224	DRT 1.0_46705
AP-225	DRT 1.0_46705
AP-274	ArubaOS 6.4.1
AP-275	DRT 1.0_46245
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	DRT 1.0_47469
RAP-155P	DRT 1.0_47469
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Montenegro

The following APs are currently supported in the Montenegro regulatory domain.

**Table 132:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 133:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 133: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1

## Morocco

The following APs are currently supported in the Morocco regulatory domain.

**Table 134:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64
802.11a (outdoor)	36 40 44 48
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64
802.11a 40MHz (outdoor)	36-40 44-48
802.11a 80MHz (indoor)	36-48 52-64
802.11a 80MHz (outdoor)	36-48
802.11a (DFS)	52 56 60 64

**Table 135:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-225	DRT 1.0_46413
RAP-3WN	DRT 1.0_47726
RAP-3WNP	DRT 1.0_47726

## Namibia

The following APs are currently supported in the Namibia regulatory domain.

**Table 136:** *Supported APs*

Device	Minimum Software Requirement
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1



## Netherlands

The following APs are currently supported in the Netherlands regulatory domain.

**Table 137:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 138:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 138: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## New Zealand

The following APs are currently supported in the New Zealand regulatory domain.

**Table 139:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	100-104 108-112 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 149-161
802.11a 80MHz (outdoor)	100-112 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 140:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-120 abg	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 140: Supported APs**

Device	Minimum Software Requirement
AP-125 abg	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-214	DRT 1.0_47156
AP-215	DRT 1.0_47156
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Nicaragua

**Table 141:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	52-64 100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 144

The following APs are currently supported in the Nicaragua regulatory domain.

**Table 142:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1

## Niger

**Table 143:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 80MHz (outdoor)	36-48 52-64

The following APs are currently supported in the Niger regulatory domain.

**Table 144:** *Supported APs*

Device	Minimum Software Requirement
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

## Nigeria

The following APs are currently supported in the Nigeria regulatory domain.

**Table 145:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	52 56 60 64 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	52-56 149-153 157-161
802.11a 80MHz (indoor)	52-64 149-161
802.11a 80MHz (outdoor)	52-64 149-161
802.11a (DFS)	52 56 60 64

**Table 146:** *Supported APs*

Device	Minimum Software Requirement
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-225	DRT 1.0_47469

## Norway

The following APs are currently supported in the Norway regulatory domain.

**Table 147: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 148: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-120abg	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-121abg	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1



**Table 148: Supported APs**

Device	Minimum Software Requirement
AP-124abg	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-125abg	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Oman

The following APs are currently supported in the Oman regulatory domain.

**Table 149: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	None
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	None
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 150: Supported APs**

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-109	DRT 1.0_47726
RAP-155	DRT 1.0_47726

## Pakistan

The following APs are currently supported in the Pakistan regulatory domain.

**Table 151:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	149 153 157 161 165
802.11g (outdoor)	None
802.11a (outdoor)	None
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	149-153 157-161
802.11g 40MHz (outdoor)	None
802.11a 40MHz (outdoor)	None
802.11a 80MHz (indoor)	149-161
802.11a 80MHz (outdoor)	None
802.11a (DFS)	None

**Table 152:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1

## Panama

The following APs are currently supported in the Panama regulatory domain.

**Table 153:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 154:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-135	DRT 1.0_47156
AP-175P	ArubaOS 6.4.1
AP-225	DRT 1.0_47156
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1

## Papua New Guinea

The following APs are currently supported in the Papua New Guinea regulatory domain.

**Table 155:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	36 40 44 48 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	36-40 44-48 149-153 157-161
802.11a 80MHz (indoor)	36-48 149-161
802.11a 80MHz (outdoor)	36-48 149-161
802.11a (DFS)	None

**Table 156:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1

## Paraguay

The following APs are currently supported in the Paraguay regulatory domain.

**Table 157:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 158:** *WebUI Fixed Issues*

Device	Minimum Software Requirement
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1

## Peru

The following APs are currently supported in the Peru regulatory domain.

**Table 159:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 116-120 124-128 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 116-128 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 144

**Table 160:** *Supported APs*

Device	Minimum Software Requirement
AP-103	DRT 1.0_47156
AP-103H	DRT 1.0_46705
AP-105	ArubaOS 6.4.1
AP-114	DRT 1.0_47156
AP-115	DRT 1.0_47156
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	DRT 1.0_47156
AP-224	DRT 1.0_47156
AP-225	DRT 1.0_47469

**Table 160:** *Supported APs*

Device	Minimum Software Requirement
RAP-108	DRT 1.0_46705
RAP-109	DRT 1.0_47469
RAP-3WN	DRT 1.0_47469



## Philippines

The following APs are currently supported in the Philippines regulatory domain.

**Table 161:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128 149-161
802.11a (DFS)	None

**Table 162:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_46245
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1

**Table 162: Supported APs**

Device	Minimum Software Requirement
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
RAP-108	DRT 1.0_45134
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Poland

The following APs are currently supported in the Poland regulatory domain.

**Table 163:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 164:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 164: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Puerto Rico

The following APs are currently supported in the Puerto Rico regulatory domain.

**Table 165:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 166:** *Supported APs*

Device	Minimum Software Requirement
AP-103H	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1

**Table 166: Supported APs**

Device	Minimum Software Requirement
AP-175DC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	<ul style="list-style-type: none"><li>• Non-DFS: ArubaOS 6.4.1</li><li>• DFS: DRT 1.0_45134</li></ul>
AP-225	<ul style="list-style-type: none"><li>• Non-DFS: ArubaOS 6.4.1</li><li>• DFS: DRT 1.0_45134</li></ul>
AP-274	DRT 1.0_44265
AP-275	DRT 1.0_44265
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Qatar

The following APs are currently supported in the Qatar regulatory domain.

**Table 167:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	149 153 157 161 165
802.11g (outdoor)	None
802.11a (outdoor)	None
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	149-153 157-161
802.11g 40MHz (outdoor)	None
802.11a 40MHz (outdoor)	None
802.11a 80MHz (indoor)	149-161
802.11a 80MHz (outdoor)	None
802.11a (DFS)	None

**Table 168:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1

**Table 168: Supported APs**

Device	Minimum Software Requirement
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1



## Romania

The following APs are currently supported in the Romania regulatory domain.

**Table 169:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 170:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 170: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Russia

The following APs are currently supported in the Russia regulatory domain.

**Table 171:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64
802.11a 80MHz (indoor)	36-48 52-64
802.11a 80MHz (outdoor)	36-48 52-64
802.11a (DFS)	None

**Table 172:** *Supported APs*

Device	Minimum Software Requirement
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-103	DRT 1.0_47726
AP-103H	DRT 1.0_47726
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 172: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_47726
AP-205	DRT 1.0_47726
AP-214	DRT 1.0_47726
AP-215	DRT 1.0_47726
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	DRT 1.0_47726
AP-275	DRT 1.0_47726
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Saudi Arabia

The following APs are currently supported in the Saudi Arabia regulatory domain.

**Table 173:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140 149 153 157 161
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 174:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_46245
AP-104	ArubaOS 6.4.1
AP-105	DRT 1.0_46245
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	DRT 1.0_46245
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 174: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Senegal

The following APs are currently supported in the Senegal regulatory domain.

**Table 175: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	None
802.11a (outdoor)	None
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	None
802.11a 40MHz (outdoor)	None
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	None
802.11a (DFS)	None

**Table 176: Supported APs**

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1

## Serbia

The following APs are currently supported in the Serbia regulatory domain.

**Table 177: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 178: Supported APs**

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-225	DRT 1.0_46705
AP-93H	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1



## Singapore

The following APs are currently supported in the Singapore regulatory domain.

**Table 179: Supported Channels**

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	36-48 52-64 100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 180: Supported APs**

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 180: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_47156
AP-214	ArubaOS 6.4.1
AP-215	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Slovak Republic

The following APs are currently supported in the Slovak Republic regulatory domain.

**Table 181:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 182:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 182: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Slovenia

The following APs are currently supported in the Slovenia regulatory domain.

**Table 183:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 184:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 184: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## South Africa

The following APs are currently supported in the South Africa regulatory domain.

**Table 185:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 186:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_46245
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	DRT 1.0_47156
AP-135	DRT 1.0_47156

**Table 186: Supported APs**

Device	Minimum Software Requirement
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_46705
AP-205	DRT 1.0_46705
AP-214	DRT 1.0_47156
AP-215	DRT 1.0_47156
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	DRT 1.0_45134
AP-275	DRT 1.0_45134
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1



## South Korea

The following APs are currently supported in the South Korea regulatory domain.

**Table 187:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 149 153 157 161
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 120 124 128 149 153 157 161
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 116-120 124-128 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	52-64 100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128

**Table 188:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1

**Table 188: Supported APs**

Device	Minimum Software Requirement
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_46245
AP-205	DRT 1.0_46245
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245
AP-224	ArubaOS 6.4.1
AP-274	DRT 1.0_45530
AP-275	DRT 1.0_45530
AP-225	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Spain

The following APs are currently supported in the Spain regulatory domain.

**Table 189:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 190:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 190: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Sri Lanka

The following APs are currently supported in the Sri Lanka regulatory domain.

**Table 191:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 132-144 149-161

**Table 192:** *Supported APs*

Device	Regulatory-Cert Version
AP-105	DRT 1.0_46245 <ul style="list-style-type: none"><li>▪ Channel 144 not available</li></ul>
AP-135	DRT 1.0_46245 <ul style="list-style-type: none"><li>▪ Channel 144 not available</li></ul>
AP-225	DRT 1.0_46245

## Sweden

The following APs are currently supported in the Sweden regulatory domain.

**Table 193:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 194:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 194: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-214	DRT 1.0_45134
AP-215	DRT 1.0_45134
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Switzerland

The following APs are currently supported in the Switzerland regulatory domain.

**Table 195:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 196:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1



**Table 196: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Taiwan

The following APs are currently supported in the Taiwan regulatory domain.

**Table 197:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	100-112 132-144 149-161
802.11a (DFS)	100 104 108 112 116 132 136 140

**Table 198:** *Supported APs*

Device	Minimum Software Requirement
AP-103	DRT 1.0_46245
AP-103H	DRT 1.0_47156
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 198: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-214	DRT 1.0_46245 Channel 165 not available
AP-215	DRT 1.0_46245 Channel 165 not available
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	DRT 1.0_47726
AP-275	DRT 1.0_47726
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Thailand

The following APs are currently supported in the Thailand regulatory domain.

**Table 199:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 200:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45134
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 200: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Trinidad and Tobago

The following APs are currently supported in the Trinidad and Tobago regulatory domain.

**Table 201:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 100-112 116-128 149-161
802.11a 80MHz (outdoor)	100-112 116-128 149-161

**Table 202:** *Supported APs*

Device	Minimum Software Requirement
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1

## Tunisia

The following APs are currently supported in the Tunisia regulatory domain.

**Table 203:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64
802.11a 80MHz (indoor)	36-48 52-64
802.11a 80MHz (outdoor)	36-48 52-64

**Table 204:** *Supported APs*

Device	Minimum Software Requirement
AP-105	DRT 1.0_47726
AP-125	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1

## Turkey

The following APs are currently supported in the Turkey regulatory domain.

**Table 205:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-120 124-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 206:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	ArubaOS 6.4.1
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1



**Table 206: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1
AP-205	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-277	DRT 1.0_47469
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## Uganda

The following APs are currently supported in the Uganda regulatory domain.

**Table 207:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 149-153
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-120 124-128 149-161
802.11a 80MHz (outdoor)	100-112 116-120 124-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140

**Table 208:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1

**Table 208:** *Supported APs*

Device	Minimum Software Requirement
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1

## Ukraine

The following APs are currently supported in the Ukraine regulatory domain.

**Table 209:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132

**Table 210:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45245
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1

**Table 210: Supported APs**

Device	Minimum Software Requirement
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_45134
AP-205	DRT 1.0_45134
AP-214	DRT 1.0_46245
AP-215	DRT 1.0_46245
AP-224	DRT 1.0_46413
AP-225	DRT 1.0_46413
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	DRT 1.0_46413
RAP-3WNP	DRT 1.0_46413

## United Arab Emirates

The following APs are currently supported in the United Arab Emirates regulatory domain.

**Table 211:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 212:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-103H	DRT 1.0_45907
AP-104	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1

**Table 212: Supported APs**

Device	Minimum Software Requirement
AP-175DC	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-204	DRT 1.0_46413
AP-205	DRT 1.0_47469
AP-214	DRT 1.0_47726
AP-215	DRT 1.0_47156
AP-224	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1
AP-274	ArubaOS 6.4.1
AP-275	ArubaOS 6.4.1
AP-68	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1

## United Kingdom

The following APs are currently supported in the United Kingdom regulatory domain.

**Table 213:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128
802.11a 80MHz (outdoor)	100-112 116-128
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 214:** *Supported APs*

Device	Minimum Software Requirement	Regulatory Certs of DFS
AP-103	ArubaOS 6.4.1	N/A
AP-103H	ArubaOS 6.4.1	N/A
AP-104	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1	ArubaOS 6.4.1



**Table 214: Supported APs**

Device	Minimum Software Requirement	Regulatory Certs of DFS
AP-135	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1	N/A
AP-205	ArubaOS 6.4.1	N/A
AP-214	DRT 1.0_45134	N/A
AP-215	DRT 1.0_45134	N/A
AP-274	ArubaOS 6.4.1	N/A
AP-275	ArubaOS 6.4.1	N/A
AP-277	DRT 1.0_47469	N/A
AP-68	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1	ArubaOS 6.4.1

## United States of America

The following APs are currently supported in the United States of America regulatory domain.

**Table 215:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 132 136 140 144 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 132-136 140-144 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 132-144 149-161
802.11a 80MHz (outdoor)	52-64 100-112 132-144 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 132 136 140 144

**Table 216:** *Supported APs*

Device	Minimum Software Requirement	Regulatory Cert for DFS
AP-103	ArubaOS 6.4.1	N/A
AP-103H	DRT 1.0_45134	N/A
AP-104	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-105	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-114	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-115	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1	ArubaOS 6.4.1

**Table 216: Supported APs**

Device	Minimum Software Requirement	Regulatory Cert for DFS
AP-134	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-175DC	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-224	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-225	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-204	ArubaOS 6.4.1	DRT 1.0_45530
AP-205	ArubaOS 6.4.1	DRT 1.0_45530
AP-214	ArubaOS 6.4.2	N/A
AP-215	ArubaOS 6.4.2	N/A
AP-274	ArubaOS 6.4.1	N/A
AP-275	ArubaOS 6.4.1	N/A
AP-277	DRT 1.0_47469	N/A
AP-68	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-108	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-109	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-155	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-155P	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-3WN	ArubaOS 6.4.1	ArubaOS 6.4.1
RAP-3WNP	ArubaOS 6.4.1	ArubaOS 6.4.1

## Uruguay

The following APs are currently supported in the Uruguay regulatory domain.

**Table 217:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	100-112 116-128 149-161
802.11a (DFS)	None

**Table 218:** *Supported APs*

Device	Minimum Software Requirement
AP-104	ArubaOS 6.4.1
AP-135	DRT 1.0_46079
AP-225	DRT 1.0_46079
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1

## Venezuela

The following APs are currently supported in the Venezuela regulatory domain.

**Table 219:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 149-161
802.11a 80MHz (outdoor)	36-48 149-161
802.11a (DFS)	52 56 60 64

**Table 220:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1
AP-175AC	ArubaOS 6.4.1
AP-175P	ArubaOS 6.4.1
AP-225	DRT 1.0_45134

## Vietnam

The following APs are currently supported in the Vietnam regulatory domain.

**Table 221:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	52-56 60-64 100-104 108-112 116-120 124-128 132-136 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 100-112 116-128 149-161
802.11a 80MHz (outdoor)	52-64 100-112 116-128 149-161
802.11a (DFS)	52 56 60 64 100 104 108 112 116 120 124 128 132 136 140

**Table 222:** *Supported APs*

Device	Minimum Software Requirement
AP-103	ArubaOS 6.4.1
AP-104	DRT 1.0_46705
AP-105	ArubaOS 6.4.1
AP-115	DRT 1.0_45134
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-134	ArubaOS 6.4.1
AP-135	ArubaOS 6.4.1

**Table 222:** *Supported APs*

Device	Minimum Software Requirement
AP-205	DRT 1.0_46705
AP-225	DRT 1.0_45134
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1
RAP-155P	DRT 1.0_47469

## Zambia

The following APs are currently supported in the Zambia regulatory domain.

**Table 223:** *Supported Channels*

Type	Channels
802.11g (indoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (indoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g (outdoor)	1 2 3 4 5 6 7 8 9 10 11 12 13
802.11a (outdoor)	36 40 44 48 52 56 60 64 149 153 157 161 165
802.11g 40MHz (indoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (indoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11g 40MHz (outdoor)	1-5 2-6 3-7 4-8 5-9 6-10 7-11 8-12 9-13
802.11a 40MHz (outdoor)	36-40 44-48 52-56 60-64 149-153 157-161
802.11a 80MHz (indoor)	36-48 52-64 149-161
802.11a 80MHz (outdoor)	36-48 52-64 149-161
802.11a (DFS)	None

**Table 224:** *Supported APs*

Device	Minimum Software Requirement
AP-105	ArubaOS 6.4.1
AP-120	ArubaOS 6.4.1
AP-121	ArubaOS 6.4.1
AP-124	ArubaOS 6.4.1
AP-125	ArubaOS 6.4.1
AP-92	ArubaOS 6.4.1
AP-93	ArubaOS 6.4.1
AP-93H	ArubaOS 6.4.1



## Zimbabwe

The following APs are currently supported in the Zimbabwe regulatory domain.

**Table 225:** *Supported APs*

Device	Minimum Software Requirement
AP-103	DRT 1.0_47726
AP-205	DRT 1.0_47726

The following sections list the changes introduced in each release of the downloadable regulatory table. Each release includes the changes introduced in previous releases. The releases are listed from newest to oldest.

- [1.0\\_47726](#)
- [1.0\\_47156](#)
- [1.0\\_46413](#)
- [1.0\\_46245](#)
- [1.0\\_45530](#)
- [1.0\\_45134](#)
- [1.0\\_44265](#)

## 1.0\_47726

This table describes the new regulatory changes to access points and channels introduced in this release.



---

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

---

**Table 226:** 1.0\_47726

Regulatory Domain	Regulatory Changes
Algeria	Support added for AP-205
Brazil	Support updated for AP-92 and AP-93
Jamacia	Support added for AP-225
Morocco	Support added for RAP-3WN and RAP-3WNP
Malasyia	Support added for AP-214
Oman	<ul style="list-style-type: none"><li>• Support added for RAP-109</li><li>• Support added for RAP-155</li></ul>
Peru	<ul style="list-style-type: none"><li>• Support added for AP-204 and AP-205</li><li>• Support added for AP-275</li><li>• Support added for RAP-3WNP</li><li>• Support added for RAP-108</li></ul>
Russia	<ul style="list-style-type: none"><li>• Support added for AP-103and AP-103H</li><li>• Support added for AP-204 and AP-205</li><li>• Support added for AP-214 and AP-215</li><li>• Support added for AP-274 and AP-275</li></ul>
South Korea	Support added for AP-103H
Taiwan	Support added for AP-274 and AP-275
Tunisia	Support updated for AP-105
United Arab Emirates	Support added for AP-214
Zimbabwe	<ul style="list-style-type: none"><li>• Support added for AP-103</li><li>• Support added for AP-205</li></ul>

## 1.0\_47726

This table describes the new regulatory changes to access points and channels introduced in this release.



---

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

---

**Table 227:** 1.0\_47726

Regulatory Domain	Regulatory Changes
Austria	Support added for AP-277
Belgium	Support added for AP-277
Botswana	Support added for AP-135
Brazil	Support added for RAP-155 and RAP-155P
Bulgaria	Support added for AP-277
Canada	Support added for AP-277
Cyprus	Support added for AP-277
Czech Republic	Support added for AP-277
Denmark	Support added for AP-277
Estonia	Support added for AP-277
Finland	Support added for AP-277
France	Support added for AP-277
Germany	Support added for AP-277
Greece	Support added for AP-277
Hungary	Support added for AP-277
Iceland	Support added for AP-277
Indonesia	Support added for AP-215
Ireland	Support added for AP-277
Italy	Support added for AP-277
Jordan	Support added for AP-103
Kazakhstan	<ul style="list-style-type: none"><li>• Support added for RAP-108 and RAP-109</li><li>• Support added for RAP-155 and RAP-155P</li></ul>
Kenya	<ul style="list-style-type: none"><li>• Support added for AP-115</li><li>• Support added for AP-205</li></ul>

**Table 227: 1.0\_47726**

Regulatory Domain	Regulatory Changes
	<ul style="list-style-type: none"><li>• Support added for AP-215</li><li>• Support added for AP-225</li><li>• Support added for AP-275</li></ul>
Latvia	Support added for AP-277
Liechtenstein	Support added for AP-277
Lithuania	Support added for AP-277
Luxembourg	Support added for AP-277
Macau	<ul style="list-style-type: none"><li>• Support updated for AP-103</li><li>• Support updated for AP-103H</li></ul>
Malaysia	Support added for AP-215
Malta	Support added for AP-277
Mexico	Support updated for RAP-155 and RAP-155P
Netherlands	Support added for AP-277
Nigeria	Service added for AP-225
Norway	Support added for AP-277
Peru	<ul style="list-style-type: none"><li>• Service updated for AP-225</li><li>• Service updated for RAP-109</li><li>• Service added for RAP-3WN</li></ul>
Poland	Support added for AP-277
Portugal	Support added for AP-277
Romania	Support added for AP-277
Slovak Republic	Support added for AP-277
Slovenia	Support added for AP-277
Spain	Support added for AP-277
Sweden	Support added for AP-277
Switzerland	Support added for AP-277
Turkey	Support added for AP-277
United Arab Emirates	Support added for AP-205

**Table 227:** 1.0\_47726

Regulatory Domain	Regulatory Changes
United Kingdom	Support added for AP-277
United States of America	Support added for AP-277
Vietnam	Support added for RAP-155P
ETSI Country Domains	<ul style="list-style-type: none"><li data-bbox="591 428 1094 459">● MAX-EIRP updated for AP-204 and AP-205</li><li data-bbox="591 470 1094 501">● MAX-EIRP updated for AP-214 and AP-215</li></ul>

## 1.0\_47156

This table describes the new regulatory changes to access points and channels introduced in this release.



---

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

---

**Table 228:** 1.0\_47156

Regulatory Domain	Regulatory Changes
Australia	Support added for AP-214 and AP-215
Bolivia	Support added for AP-135
Canada	DFS bands enabled for AP-214 and AP-215 DFS bands enabled for AP-274 and AP-275
China	Support updated for RAP-3WN and RAP-3WNP
Costa Rica	Support added for AP-114 and AP-115 Support added for AP-204 and AP-205 Support added for AP-224 and AP-225 Support updated for RAP-108 and RAP-109 Support added for RAP-3WN and RAP-3WNP Support added for AP-274 and AP-275
Kuwait	Support added for AP-225
Lebanon	Support added for AP-225
Macedonia	Support added for AP-225
Mexico	Support updated for AP-103
New Zealand	Support added for AP-214 and AP-215
Panama	Support added for AP-225 Support added for AP-135
Peru	Support added for AP-103 Support added for AP-114 and AP-115 Support updated for AP-135 Support added for RAP-109 Support added for RAP-109
Singapore	Support added for AP-204

**Table 228:** 1.0\_47156

Regulatory Domain	Regulatory Changes
South Africa	Support updated for AP-134 and AP-135 Support added for AP-214 and AP-215
Taiwan	Support added for AP-103H
United Arab Emirates	Support added for AP-215



## 1.0\_46705

This table describes the new regulatory changes to access points and channels introduced in this release.



---

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

---

**Table 229:** 1.0\_46705

Regulatory Domain	Regulatory Changes
Indonesia	<ul style="list-style-type: none"><li>• Support added for AP-103H</li><li>• Support updated for AP-204</li></ul>
Macau	Support added for AP-103
Macedonia	Support added for AP-225
Malaysia	Support added for AP-103H
Mexico	<ul style="list-style-type: none"><li>• Support updated for RAP-155 and RAP-155P</li><li>• Support added for AP-215</li><li>• Support updated for AP-224 and AP-225</li></ul>
Panama	<ul style="list-style-type: none"><li>• Support added for AP-135</li><li>• Support added for AP-225</li></ul>
Peru	<ul style="list-style-type: none"><li>• Support added for AP-103H</li><li>• Support added for RAP-108</li></ul>
Serbia	Support added for AP-225
South Africa	Support updated for AP-204 and AP-205
Vietnam	<ul style="list-style-type: none"><li>• Support updated for AP-104</li><li>• Support added for AP-205</li></ul>

## 1.0\_46413

This table describes the new regulatory changes to access points and channels introduced in this release.



---

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

---

**Table 230:** 1.0\_46413

Regulatory Domain	Regulatory Changes
Indonesia	Support updated for AP-204
Japan	Support updated for AP-274 and AP-275
Macau	Support added for AP-103
Mexico	Support added for AP-103H
Morocco	Support updated for AP-225
Namibia	Support added for AP-224 and AP-225
Peru	<ul style="list-style-type: none"><li>• Support added for AP-103H</li><li>• Support added for RAP-108</li></ul>
Ukraine	<ul style="list-style-type: none"><li>• Support updated for AP-224 and AP-225</li><li>• Support added for RAP-3WN and RAP-3WNP</li></ul>
United Arabic Emirates	Support added for AP-204

## 1.0\_46245

This table describes the new regulatory changes to access points and channels introduced in this release.



---

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

---

**Table 231:** 1.0\_46245

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-204 and AP-205
Bahrain	Support added for AP-225
Brazil	Support added for AP-204 and AP-205
Canada	DFS channels added for AP-204 and AP-205
Chile	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
China	Support added for AP-214 and AP-215
Costa Rica	Support added for RAP-108 and RAP-109
Egypt	Support added for AP-103H
Hong Kong	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
India	Support added for AP-214 and AP-215
Indonesia	<ul style="list-style-type: none"><li>Support removed for AP-105</li><li>Support added for RAP-108 and RAP-109</li><li>Support added for AP-115</li><li>Support removed for AP-135</li><li>Support added for RAP-155 and RAP-155P</li><li>Support added for AP-175P</li><li>Support added for AP-225</li></ul>
Israel	<ul style="list-style-type: none"><li>Support added for AP-103</li><li>Support added for AP-104</li><li>Support added for AP-204 and AP-205</li></ul>
Japan	Support added for AP-274 and AP-275
Malaysia	Support added for AP-204 and AP-205
Mauritius	Support added for AP-135

**Table 231: 1.0\_46245**

Regulatory Domain	Regulatory Changes
Mexico	<ul style="list-style-type: none"><li>● Support added for RAP-155 and RAP-155P</li><li>● Support added for AP-204 and AP-205</li><li>● Support added for AP-275</li></ul>
Morocco	Support added for AP-225
Philippines	<ul style="list-style-type: none"><li>● Support added for AP-103H</li><li>● Support added for AP-214 and AP-215</li></ul>
Qatar	Support added for AP-214 and AP-215
Saudi Arabia	<ul style="list-style-type: none"><li>● Support added for AP-103H</li><li>● Support added for AP-105</li><li>● Support added for AP-214 and AP-215</li></ul>
South Africa	<ul style="list-style-type: none"><li>● Support added for AP-103H</li><li>● Support added for AP-204 and AP-205</li></ul>
South Korea	<ul style="list-style-type: none"><li>● Support added for AP-204 and AP-205</li><li>● Support added for AP-214 and AP-215</li></ul>
Sri Lanka	<ul style="list-style-type: none"><li>● Support added for AP-105</li><li>● Channel 144 removed for AP-105</li><li>● Support added for AP-135</li><li>● Channel 144 removed for AP-135</li><li>● Support added for AP-225</li></ul>
Taiwan	<ul style="list-style-type: none"><li>● Support added for AP-103</li><li>● Support added for AP-214 and AP-215</li><li>● Channel 165 removed for AP-214 and AP-215</li></ul>
Ukraine	<ul style="list-style-type: none"><li>● Support added for AP-103H</li><li>● Support added for AP-214 and AP-215</li></ul>
United Arab Emirates	Support added for AP-103H
Uruguay	<ul style="list-style-type: none"><li>● Support added for AP-135</li><li>● Support added for AP-225</li></ul>
Vietnam	Support added for AP-104

## 1.0\_45530

This table describes the new regulatory changes to access points and channels introduced in this release.



---

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

---

**Table 232:** 1.0\_45530

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-274 and AP-275
Australia	Support added for AP-103H
Bolivia	Support added for AP-225
Botswana	Support added for AP-225
Brazil	Support added for AP-103
India	Support added for AP-204 and AP-205
Japan	Support added for AP-103H
New Zealand	Support added for AP-103H
Singapore	<ul style="list-style-type: none"><li>• Support added for AP-214 and AP-215</li><li>• Support added for AP-103H</li></ul>
South Korea	Support added for AP-274 and AP-275
Taiwan	Support added for AP-204 and AP-205
Venezuela	Channels 36-48 for 802.11a 80MHz (outdoor)

## 1.0\_45134

This table describes the new regulatory changes to access points and channels introduced in this release.



This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

**Table 233:** 1.0\_45134

Regulatory Domain	Regulatory Changes
Argentina	Support added for AP-103
Australia	Support added for AP-204 and AP-205
Austria	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
Bahamas	<ul style="list-style-type: none"><li>Support added for AP-204 and AP-205</li><li>Support added for AP-224 and AP-225</li><li>Support added for AP-274 and AP-275</li></ul>
Bosnia/Herzegovina	Support added for AP-103H
Belgium	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
Bulgaria	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
Canada	Support added for AP-103H Support added for AP-214 and AP-215
China	Support added for AP-275
Colombia	<ul style="list-style-type: none"><li>FCC DFS channels added to AP-224 and AP-225</li><li>Support added for AP-103H</li></ul>
Croatia	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
Cyprus	Support added for AP-103H
Czech Republic	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
Denmark	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
Dominica Republic	FCC DFS channels added to AP-224 and AP-225
Estonia	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
Finland	<ul style="list-style-type: none"><li>Support added for AP-103H</li><li>Support added for AP-214 and AP-215</li></ul>
France	<ul style="list-style-type: none"><li>Support added for AP-103H</li></ul>

**Table 233: 1.0\_45134**

Regulatory Domain	Regulatory Changes
	<ul style="list-style-type: none"> <li>Support added for AP-214 and AP-215</li> </ul>
Germany	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Hong Kong	<ul style="list-style-type: none"> <li>Support added for AP-204 and</li> <li>Channels 141-165 enabled for AP-120, AP-121, AP-124, and AP-125</li> </ul>
Hungary	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
India	Support added for AP-274 and AP-275
Ireland	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Israel	<ul style="list-style-type: none"> <li>Support ended for 802.11g 40MHz (indoor) 8-12 and 9-13</li> <li>Support ended for 802.11g 40MHz (outdoor) 8-12 and 9-13</li> </ul>
Italy	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Japan	Support added for AP-204 and AP-205
Israel	Support added for AP-204 and AP-205
Latvia	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Lithuania	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Luxembourg	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Macedonia	<ul style="list-style-type: none"> <li>Support added for AP-204 and AP-205</li> <li>Support added for AP-103H</li> </ul>
Malta	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Maritime	Support added for this domain
Maritime Offshore	Support added for this domain
Mauritius	Support added for AP-224 and AP-225
Mexico	Support added for AP-103
Montenegro	Support added for AP-103H
Netherlands	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>

**Table 233: 1.0\_45134**

Regulatory Domain	Regulatory Changes
New Zealand	Support added for AP-204and AP-205
Philippines	<ul style="list-style-type: none"> <li>Support added for RAP-108</li> <li>Support added for AP-204and AP-205</li> </ul>
Poland	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Portugal	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Puerto Rico	<ul style="list-style-type: none"> <li>FCC DFS channels added to AP-224 and AP-225</li> <li>Support added for AP-103H</li> </ul>
Qatar	Support added for AP-204and AP-205
Romania	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Saudi Arabia	Support added for AP-204and AP-205
Slovakia	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
Slovenia	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
South Africa	Support added for AP-274 and AP-275
South Korea	Support added for AP-274 and AP-275
Sweden	Support added for AP-103H
Thailand	Support added for AP-103H
Ukraine	Support added for AP-204and AP-205
United Kingdom	<ul style="list-style-type: none"> <li>Support added for AP-103H</li> <li>Support added for AP-214 and AP-215</li> </ul>
United States of America	Support added for AP-103H Support added for AP-214 and AP-215
Venezuela	Support added for AP-225
Vietnam	<ul style="list-style-type: none"> <li>Support added for AP-225</li> <li>Support added for AP-115</li> </ul>



## 1.0\_44265

This table describes the new regulatory changes to access points and channels introduced in this release.



---

This release includes all regulatory domains and access points supported in ArubaOS 6.4.1.0 and newer.

---

**Table 234:** *1.0\_44265*

Regulatory Domain	Regulatory Changes
Chile	Support added for AP-270 Series
Hong Kong	Support added for AP-220 Series
Puerto Rico	Support added for AP-270 Series