HPE Aruba Networking CX 6100 Switch Series

What's new

- It simplifies IT operations with next-gen Layer 2 switch series that provides entry-level, reliable, and convenient wired access connectivity
- The CX 6100 series provides right size with 12, 24, and 48-port 1U models with convenient built-in 1/10GbE uplinks and up to 740W of Class 4 PoE
- It has compact and fan-less 12-port PoE model for space-constrained deployments
- The CX 6100 provides flexibility to manage and simplify configurations with HPE Aruba Networking Central, HPE Aruba Networking Switch Multi-Edit Software, easy to use Web GUI, or industry-standard CLI

Overview

The HPE Aruba Networking CX 6100 Switch Series is a modern family of entry-level access switches ideal for branch offices, mid-market enterprises, and SMB networks. Designed for reliable, simple, and secure access, this switch family provides a convenient wired access solution for enterprise networks supporting Internet of Things (IoT), mobile, and cloud applications.

Prepare your network for future demands with a powerful ASIC and the programmable HPE Aruba Networking CX Switch Operating System to deliver a more consistent, more efficient operator experience. This Layer 2 switch series has convenient built-in high speed uplinks with up to 740W of IEEE 802.3at Class 4 PoE to support IoT devices such as security cameras and wireless APs. A compact and fanless 12-port model is ideal for use in quiet workspaces. With robust quality of service (QoS), support for static routing, and IPv6, these switches also simplify ownership with no switch software licensing requirements.

– It offers scalability with a 6-member switch virtual switching framework (VSF) stacking

Features

Entry-level Layer 2 access switches

The HPE Aruba Networking CX 6100 Switch Series offers gigabit connectivity with high-speed uplinks and optional PoE to provide entry-level, reliable, and convenient wired access connectivity for enterprise branch office and SMB networks.

The switch series delivers a simple, consistent operator experience with the HPE Aruba Networking CX Switch Operating System (AOS-CX) used across HPE Aruba Networking CX switching platforms.

It has fully-managed enterprise-class switches deliver Layer 2 capabilities with support for static routing, access control lists (ACLs), robust quality of service (QoS), traffic prioritization, sFlow®, and IPv6.

The CX 6100 series provides right-size deployment with choice of 12, 24, and 48-port 1U models with convenient built-in 1/10GbE uplinks and up to 740W of Class 4 PoE.

It simplifies ownership with no switch software licensing or subscriptions required.

AI-ready performance and power

The HPE Aruba Networking CX 6100 Switch Series is designed with a dedicated ASIC that delivers very low latency, increased packet buffering, and adaptive power consumption needed for AI, Wi-Fi 7, and Internet of Things (IoT) requirements.

It has up to 740W IEEE 802.3at Class 4 PoE with up to 30W per port supports newer Wi-Fi 7 and PoE devices.

The four built-in wire speed 1/10GbE uplinks mitigate bottlenecks at the access layer where users and devices connect.

Simplified configuration and management

The HPE Aruba Networking CX 6100 Switch Series provides flexibility to manage and simplify configurations with HPE Aruba Networking Central, HPE Aruba Networking Switch Multi-Edit Software, easy-to-use web GUI, or industry-standard CLI.

HPE Aruba Networking Switch Multi-Edit Software introduces automation that allows for rapid network-wide changes and verifies policy conformance post network updates.

The switch series offers unified management across wired, wireless, and WAN using HPE Aruba Networking Central.

It reduces manual IT operation tasks around initial deployment or on-going configuration changes to accommodate adds, moves, and changes with colorless ports using local user roles and local MAC authentication (LMA).

The CX 6100 series is ready for software-defined networking with REST APIs for fine-grained programmability of network tasks.

It offers virtual switching framework (VSF) stacking - Scale and simplicity

It support for up to six switches (or members) in a stack through chain or ring topology.

It offers the flexibility to create stacks that span longer distances such as hundreds of meters across campuses to kilometers between sites.

It has the flexibility to mix 24 and 48-port modular and fixed CX 6100 models.

It has a simplified configuration and management as the switches act as a single chassis when stacked.

Technical specifications	HPE Aruba Networking CX 6100 Switch Series
Power consumption	Maximum Power (w/o PoE): 49.7W Maximum Power (w/ PoE): 890W Depending on model
Input voltage	100–127 VAC / 200–240 VAC
Ports	12, 24, or 48 10/100/1000BASE-T ports, 1U models with convenient built-in 1/10GbE uplinks depending on model
Latency	1 Gbps: 2.3 µSec, 10 Gbps: 2.6 µSec maximum, depending on model
Switching capacity	176 Gbps maximum, depending on model
Throughput	Up to 98.6 Mpps, depending on model
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1016 MHz Memory: 4 GB DDR3 Flash: 16 GB eMMC
Power supply	Fixed power supply
PoE capability	Up to 740W of Class 4 PoE maximum, depending on model
Operating temperature	Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate by 1°C for every 1000 ft (305m) from 5000 ft (1.5 km) to 10000 ft (3.0 km)
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software
Warranty	Limited lifetime warranty. See the warranty duration.
Fans	Fixed fans

SKU comparison

	HPE Aruba Networking CX 6100 12G Class4 PoE 2G/2SFP+ 139W Switch (JL679A)	HPE Aruba Networking CX 6100 24G 4SFP+ Switch (JL678A)	HPE Aruba Networking CX 6100 24G Class4 PoE 4SFP+ 370W Switch (JL677A)	HPE Aruba Networking CX 6100 48G 4SFP+ Switch (JL676A)	HPE Aruba Networking CX 6100 48G Class4 PoE 4SFP+ 370W Switch (JL675A)
Differentiator	Non-PoE	Non-PoE	Class 4 PoE/PoE+	Non-PoE	Class 4 PoE/PoE+
Power consumption	Max. Power (w/o PoE): 21.9W Max. Power (w/ PoE): 170W	Max. Power (w/o PoE): 33W	Max. Power (w/o PoE): 32.7W Max. Power (w/ PoE): 455W	Max. Power: 44.2W	Max. Power (w/o PoE): 45W Max. Power (w/ PoE): 480W
Input voltage	100–127 VAC / 200–240 VAC				
Ports	12 x 10/100/1000BASE-T ports 2 x 1G/10G SFP ports 2 x 1GbE ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port	24 x 10/100/1000BASE-T ports 4 x 1G/10G SFP ports 1 x USB-C console port 1 x USB Type-A host port	24 x 10/100/1000BASE-T ports 4 x 1G/10G SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port	48 x 10/100/1000BASE-T ports 4 x 1G/10G SFP ports 1 x USB-C console port 1 x USB Type-A host port	48 x 10/100/1000BASE-T ports 4 x 1G/10G SFP ports Supports PoE standards IEEE 802.3af, 802.3at 1 x USB-C console port 1 x USB Type-A host port
Latency	1 Gbps: 2.3 Sec , 10 Gbps: 2.6 Sec	1 Gbps: 1.5 Sec , 10 Gbps: 1.8 Sec	1 Gbps: 1.5 Sec , 10 Gbps: 1.8 Sec	1 Gbps: 1.9 Sec , 10 Gbps: 1.8 Sec	1 Gbps: 1.9 Sec , 10 Gbps: 1.8 Sec
Switching capacity	68 Gbps	128 Gbps	128 Gbps	176 Gbps	176 Gbps
Throughput	45.1 Mpps	95.2 Mpps	95.2 Mpps	98.6 Mpps	98.6 Mpps
Memory and processor	Dual Core ARM Cortex A9 @ 1016 Mhz 4 GB DDR3, maximum, depending on model 16 GB eMMC				
Power supply	Fixed power supply				
PoE capability	139W Class 4 PoE/PoE+	Non-PoE model	370W Class 4 PoE/PoE+	Non-PoE model	370W Class 4 PoE/PoE+

	HPE Aruba Networking CX 6100 12G Class4 PoE 2G/2SFP+ 139W Switch (JL679A)	HPE Aruba Networking CX 6100 24G 4SFP+ Switch (JL678A)	HPE Aruba Networking CX 6100 24G Class4 PoE 4SFP+ 370W Switch (JL677A)	HPE Aruba Networking CX 6100 48G 4SFP+ Switch (JL676A)	HPE Aruba Networking CX 6100 48G Class4 PoE 4SFP+ 370W Switch (JL675A)
Operating temperature	Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate by 1°C for every 1000 ft (305m) from 5000 ft (1.5 km) to 10000 ft (3.0 km)				
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software				
Warranty	Limited lifetime warranty. See the warranty duration.				
Fans	Fixed fans				

	HPE Aruba Networking CX 6100 48G Class4 PoE 4SFP+ 740W Switch (R9Y04A)
Differentiator	Class 4 PoE/PoE+
Power consumption	Max. Power (w/o PoE): 49.7W Max. Power (w/ PoE): 890W
Input voltage	100–127 VAC / 200–240 VAC
Ports	48x 10/100/1000BASE-T Class 4 PoE ports Supports PoE standards IEEE 802.3af, 802.3at 1x USB-C console port 1x USB Type-A host port
Latency	1 Gbps: 1.9 Sec, 10 Gbps: 1.8 Sec
Switching capacity	176 Gbps
Throughput	98.6 Mpps
Memory and processor	CPU: Dual-core Arm® Cortex®-A9 @ 1016 MHz Memory: 4 GB DDR3 Flash: 16 GB eMMC
Power supply	Fixed power supply
PoE capability	740W of Class 4 PoE
Operating temperature	Maximum of 32°F to 113°F (0°C to 45°C) up to 5000 ft (1.5 km) derate by 1°C for every 1000 ft (305m) from 5000 ft (1.5 km) to 10000 ft (3.0 km)
Management features	Management flexibility with support for HPE Aruba Networking Central, easy-to-use Web GUI, CLI, and HPE Aruba Networking Switch Multi-Edit Software
Warranty	Limited lifetime warranty. See the warranty duration.
Fans	Fixed fans

Related Options

The following options are available for these series:

SKU	Description
Cables/Cable Kits	
R9J32A	HPE Aruba Networking USB-A reversible to USB-C PC-to-Switch 3m Cable
R9J33A	HPE Aruba Networking USB-C to USB-C PC-to-Switch 3m Cable
JL742A	HPE Aruba Networking X511 12-port Cable Guard
HPE Aruba Networking Software	
JL639AAE	HPE Aruba Networking NetEdit Single Node 1yr Subscription E-STU
JL640AAE	HPE Aruba Networking NetEdit Single Node 3yr Subscription E-STU
Mounting Rack/Rail Options	
J9583B	HPE Aruba Networking X414 1U Universal 4-post Rack Mount Kit
Switches	
JL258A	HPE Aruba Networking 2930F 8G PoE+ 2SFP+ Switch
JL693A	HPE Aruba Networking 2930F 12G PoE+ 2G/2SFP+ Switch
JL662A	HPE Aruba Networking CX 6300M 24-port 1GbE Class 4 PoE and 4-port SFP56 Switch
JL664A	HPE Aruba Networking CX 6300M 24-port 1GbE and 4-port SFP56 Switch
JL660A	HPE Aruba Networking CX 6300M 24-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch
JL658A	HPE Aruba Networking CX 6300M 24-port SFP+ and 4-port SFP56 Switch
JL661A	HPE Aruba Networking CX 6300M 48-port 1GbE Class 4 PoE and 4-port SFP56 Switch
JL663A	HPE Aruba Networking CX 6300M 48-port 1GbE and 4-port SFP56 Switch
JL659A	HPE Aruba Networking CX 6300M 48-port HPE Smart Rate 1/2.5/5GbE Class 6 PoE and 4-port SFP56 Switch
JL762A	HPE Aruba Networking CX 6300M 48p 1GbE 4p SFP56 Power-to-Port 2 Fan Trays 1 PSU Bundle
Transceiver Options	
J4859D	HPE Aruba Networking 1G SFP LC LX 10km SMF Transceiver
J4858D	HPE Aruba Networking 1G SFP LC SX 500m OM2 MMF Transceiver
J8177E	HPE Aruba Networking 1G SFP RJ45 100m Cat5e Transceiver
S2P31A	HPE Aruba Networking 10G LR SFP+ LC 10km SMF C-Class Transceiver
J9151E	HPE Aruba Networking 10G SFP+ LC LR 10km SMF Transceiver
J9150D	HPE Aruba Networking 10G SFP+ LC SR 300m OM3 MMF Transceiver
J9281D	HPE Aruba Networking 10G SFP+ to SFP+ 1m Direct Attach Copper Cable

J9283D	HPE Aruba Networking 10G SFP+ to SFP+ 3m Direct Attach Copper Cable
S2P30A	HPE Aruba Networking 10G SR SFP+ LC 400m OM4 MMF C-Class Transceiver

Related Services

The following services are available for these series:

SKU	Description
Technology Services	
H83A1E	HPE Aruba Networking 1Y 24x7 Technical Support 6100 48G+ 740W SVC
H83G4E	HPE Aruba Networking 1Y 24x7 Technical Support Volume Tier 26100 48G+ 740W SVC
HV2L5E	HPE Aruba Networking 1Y Software+Technical Support 6100 12G CL4 Switch SVC
HV1L9E	HPE Aruba Networking 1Y Software+Technical Support 6100 24G CL4 Switch SVC
HV1Y7E	HPE Aruba Networking 1Y Software+Technical Support 6100 24G Switch SVC
HV0M3E	HPE Aruba Networking 1Y Software+Technical Support 6100 48G CL4 Switch SVC
HV0Z1E	HPE Aruba Networking 1Y Software+Technical Support 6100 48G Switch SVC
HV2R7E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 12G CL4 Switch SVC
HV1S1E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 24G CL4 Switch SVC
HV2D9E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 24G Switch SVC
HV0S5E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 48G CL4 Switch SVC
HV1E3E	HPE Aruba Networking 1Y Software+Technical Support Vol T2 6100 48G Switch SVC
H83B4E	HPE Aruba Networking 3Y 24x7 Technical Support 6100 48G+ 740W SVC
H83H9E	HPE Aruba Networking 3Y 24x7 Technical Support Volume Tier 26100 48G+ 740W SVC
HV2M5E	HPE Aruba Networking 3Y Software+Technical Support 6100 12G CL4 Switch SVC
HV1M9E	HPE Aruba Networking 3Y Software+Technical Support 6100 24G CL4 Switch SVC
HV1Z7E	HPE Aruba Networking 3Y Software+Technical Support 6100 24G Switch SVC
HV0N3E	HPE Aruba Networking 3Y Software+Technical Support 6100 48G CL4 Switch SVC
HV1A1E	HPE Aruba Networking 3Y Software+Technical Support 6100 48G Switch SVC
HV2T2E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 12G CL4 Switch SVC
HV1T6E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 24G CL4 Switch SVC
HV2F4E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 24G Switch SVC
HV0U0E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 48G CL4 Switch SVC
HV1F8E	HPE Aruba Networking 3Y Software+Technical Support Vol T2 6100 48G Switch SVC
H83E0E	HPE Aruba Networking 5Y 24x7 Technical Support 6100 48G+ 740W SVC
H83L9E	HPE Aruba Networking 5Y 24x7 Technical Support Volume Tier 26100 48G+ 740W SVC

HV2P5E	HPE Aruba Networking 5Y Software+Technical Support 6100 12G CL4 Switch SVC
HV1P9E	HPE Aruba Networking 5Y Software+Technical Support 6100 24G CL4 Switch SVC
HV2B7E	HPE Aruba Networking 5Y Software+Technical Support 6100 24G Switch SVC
HV0Q3E	HPE Aruba Networking 5Y Software+Technical Support 6100 48G CL4 Switch SVC
HV1C1E	HPE Aruba Networking 5Y Software+Technical Support 6100 48G Switch SVC
HV2W2E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 12G CL4 Switch SVC
HV1W6E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 24G CL4 Switch SVC
HV2J4E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 24G Switch SVC
HV0X0E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 48G CL4 Switch SVC
HV1J8E	HPE Aruba Networking 5Y Software+Technical Support Vol T2 6100 48G Switch SVC
HV2L0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 12G CL4 Switch SVC
HV1L4E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 24G CL4 Switch SVC
HV1Y2E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 24G Switch SVC
HV0L8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 48G CL4 Switch SVC
HV0Y6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 48G Switch SVC
H82Z5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch 6100 48G+ 740W SVC
HV2R2E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 12G CL4 Switch SVC
HV1R6E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 24G CL4 Switch SVC
HV2D4E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 24G Switch SVC
HV0S0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 48G CL4 Switch SVC
HV1D8E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 48G Switch SVC
H83F9E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T1 6100 48G+ 740W SVC
HV2R3E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 12G CL4 Switch SVC
HV1R7E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 24G CL4 Switch SVC
HV2D5E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 24G Switch SVC
HV0S1E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 48G CL4 Switch SVC
HV1D9E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 48G Switch SVC
H83G0E	HPE Aruba Networking Foundational Care 1Y 4HR Exch Vol T2 6100 48G+ 740W SVC
HV2L3E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 12G CL4 Switch SVC
HV1L7E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 24G CL4 Switch SVC
HV1Y5E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 24G Switch SVC
HV0M1E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 48G CL4 Switch SVC
HV0Y9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 48G Switch SVC
H82Z9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite 6100 48G+ 740W SVC
HV2L4E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 12G CL4 Switch SVC
HV1L8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 24G CL4 Switch SVC

HV1Y6E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 24G Switch SVC
HV0M2E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 48G CL4 Switch SVC
HV0Z0E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite CDMR 6100 48G Switch SVC
HY2R5E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 12G CL4 SVC
HY2N9E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 24G CL4 SVC
HY2Q2E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 24G SVC
HY2L3E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 48G CL4 SVC
HY2M6E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 48G SVC
H82Z8E	HPE Aruba Networking Foundational Care 1Y 4HR Onsite Hardware Only 6100 48G+ 740W SVC
H83A0E	HPE Aruba Networking Foundational Care 1Y 24x7 CDMR 6100 48G+ 740W SVC
HV2L6E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 12G CL4 Switch SVC
HV1M0E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 24G CL4 Switch SVC
HV1Y8E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 24G Switch SVC
HV0M4E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 48G CL4 Switch SVC
HV0Z2E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour 6100 48G Switch SVC
HV2L7E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 12G CL4 Switch SVC
HV1M1E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 24G CL4 Switch SVC
HV1Y9E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 24G Switch SVC
HV0M5E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 48G CL4 Switch SVC
HV0Z3E	HPE Aruba Networking Foundational Care 1Y CTR 6-Hour CDMR 6100 48G Switch SVC
H83A2E	HPE Aruba Networking Foundational Care 1Y CTR 6100 48G+ 740W SVC
H83A3E	HPE Aruba Networking Foundational Care 1Y CTR CDMR 6100 48G+ 740W SVC
H82Z6E	HPE Aruba Networking Foundational Care 1Y NBD 6100 48G+ 740W SVC
H82Z7E	HPE Aruba Networking Foundational Care 1Y NBD CDMR 6100 48G+ 740W SVC
HV2K9E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 12G CL4 Switch SVC
HV1L3E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 24G CL4 Switch SVC
HV1Y1E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 24G Switch SVC
HV0L7E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 48G CL4 Switch SVC
HV0Y5E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 48G Switch SVC
H82Z3E	HPE Aruba Networking Foundational Care 1Y NBD Exch 6100 48G+ 740W SVC
HY2R4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 12G CL4 SVC
HY2N8E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 24G CL4 SVC
HY2Q1E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 24G SVC
HY2L2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 48G CL4 SVC
HY2M5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 48G SVC
H82Z4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Hardware Only 6100 48G+ 740W SVC

HV2Q8E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 12G CL4 Switch SVC
HV1R2E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 24G CL4 Switch SVC
HV2D0E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 24G Switch SVC
HV0R6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 48G CL4 Switch SVC
HV1D4E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 48G Switch SVC
H83F5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T1 6100 48G+ 740W SVC
HV2Q9E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 12G CL4 Switch SVC
HV1R3E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 24G CL4 Switch SVC
HV2D1E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 24G Switch SVC
HV0R7E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 48G CL4 Switch SVC
HV1D5E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 48G Switch SVC
H83F6E	HPE Aruba Networking Foundational Care 1Y NBD Exch Vol T2 6100 48G+ 740W SVC
HV2L1E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 12G CL4 Switch SVC
HV1L5E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 24G CL4 Switch SVC
HV1Y3E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 24G Switch SVC
HV0L9E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 48G CL4 Switch SVC
HV0Y7E	HPE Aruba Networking Foundational Care 1Y NBD Onsite 6100 48G Switch SVC
HV2L2E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 12G CL4 Switch SVC
HV1L6E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 24G CL4 Switch SVC
HV1Y4E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 24G Switch SVC
HV0M0E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 48G CL4 Switch SVC
HV0Y8E	HPE Aruba Networking Foundational Care 1Y NBD Onsite CDMR 6100 48G Switch SVC
HV2L9E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 12G CL4 Switch SVC
HV1M3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 24G CL4 Switch SVC
HV1Z1E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 24G Switch SVC
HV0M7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 48G CL4 Switch SVC
HV0Z5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 48G Switch SVC
H83A6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch 6100 48G+ 740W SVC
HV2S6E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 12G CL4 Switch SVC
HV1T0E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 24G CL4 Switch SVC
HV2E8E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 24G Switch SVC
HV0T4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 48G CL4 Switch SVC
HV1F2E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 48G Switch SVC
H83H3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T1 6100 48G+ 740W SVC
HV2S7E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 12G CL4 Switch SVC
HV1T1E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 24G CL4 Switch SVC

HV2E9E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 24G Switch SVC
HV0T5E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 48G CL4 Switch SVC
HV1F3E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 48G Switch SVC
H83H4E	HPE Aruba Networking Foundational Care 3Y 4HR Exch Vol T2 6100 48G+ 740W SVC
HV2M3E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 12G CL4 Switch SVC
HV1M7E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 24G CL4 Switch SVC
HV1Z5E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 24G Switch SVC
HV0N1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 48G CL4 Switch SVC
HV0Z9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 48G Switch SVC
H83B2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite 6100 48G+ 740W SVC
HV2M4E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 12G CL4 Switch SVC
HV1M8E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 24G CL4 Switch SVC
HV1Z6E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 24G Switch SVC
HV0N2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 48G CL4 Switch SVC
HV1A0E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite CDMR 6100 48G Switch SVC
HY2R8E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 12G CL4 SVC
HY2P2E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 24G CL4 SVC
HY2Q5E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 24G SVC
HY2L6E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 48G CL4 SVC
HY2M9E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 48G SVC
H83B1E	HPE Aruba Networking Foundational Care 3Y 4HR Onsite Hardware Only 6100 48G+ 740W SVC
H83B3E	HPE Aruba Networking Foundational Care 3Y 24x7 CDMR 6100 48G+ 740W SVC
HV2M6E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 12G CL4 Switch SVC
HV1N0E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 24G CL4 Switch SVC
HV1Z8E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 24G Switch SVC
HV0N4E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 48G CL4 Switch SVC
HV1A2E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour 6100 48G Switch SVC
HV2M7E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 12G CL4 Switch SVC
HV1N1E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 24G CL4 Switch SVC
HV1Z9E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 24G Switch SVC
HV0N5E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 48G CL4 Switch SVC
HV1A3E	HPE Aruba Networking Foundational Care 3Y CTR 6-Hour CDMR 6100 48G Switch SVC
H83B5E	HPE Aruba Networking Foundational Care 3Y CTR 6100 48G+ 740W SVC
H83B6E	HPE Aruba Networking Foundational Care 3Y CTR CDMR 6100 48G+ 740W SVC
H83A7E	HPE Aruba Networking Foundational Care 3Y NBD 6100 48G+ 740W SVC
H83A8E	HPE Aruba Networking Foundational Care 3Y NBD CDMR 6100 48G+ 740W SVC

HV2L8E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 12G CL4 Switch SVC
HV1M2E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 24G CL4 Switch SVC
HV1Z0E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 24G Switch SVC
HV0M6E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 48G CL4 Switch SVC
HV0Z4E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 48G Switch SVC
H83A5E	HPE Aruba Networking Foundational Care 3Y NBD Exch 6100 48G+ 740W SVC
HY2R6E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 12G CL4 SVC
HY2P0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 24G CL4 SVC
HY2Q3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 24G SVC
HY2L4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 48G CL4 SVC
HY2M7E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 48G SVC
H83A4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Hardware Only 6100 48G+ 740W SVC
HV2S2E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 12G CL4 Switch SVC
HV1S6E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 24G CL4 Switch SVC
HV2E4E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 24G Switch SVC
HV0T0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 48G CL4 Switch SVC
HV1E8E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 48G Switch SVC
H83G9E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T1 6100 48G+ 740W SVC
HV2S3E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 12G CL4 Switch SVC
HV1S7E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 24G CL4 Switch SVC
HV2E5E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 24G Switch SVC
HV0T1E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 48G CL4 Switch SVC
HV1E9E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 48G Switch SVC
H83H0E	HPE Aruba Networking Foundational Care 3Y NBD Exch Vol T2 6100 48G+ 740W SVC
HV2M0E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 12G CL4 Switch SVC
HV1M4E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 24G CL4 Switch SVC
HV1Z2E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 24G Switch SVC
HV0M8E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 48G CL4 Switch SVC
HV0Z6E	HPE Aruba Networking Foundational Care 3Y NBD Onsite 6100 48G Switch SVC
HV2M1E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 12G CL4 Switch SVC
HV1M5E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 24G CL4 Switch SVC
HV1Z3E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 24G Switch SVC
HV0M9E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 48G CL4 Switch SVC
HV0Z7E	HPE Aruba Networking Foundational Care 3Y NBD Onsite CDMR 6100 48G Switch SVC
HV2N9E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 12G CL4 Switch SVC
HV1P3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 24G CL4 Switch SVC

HV2B1E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 24G Switch SVC
HV0P7E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 48G CL4 Switch SVC
HV1B5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 48G Switch SVC
H83D2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch 6100 48G+ 740W SVC
HV2V6E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 12G CL4 Switch SVC
HV1W0E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 24G CL4 Switch SVC
HV2H8E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 24G Switch SVC
HV0W4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 48G CL4 Switch SVC
HV1J2E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 48G Switch SVC
H83L3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T1 6100 48G+ 740W SVC
HV2V7E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 12G CL4 Switch SVC
HV1W1E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 24G CL4 Switch SVC
HV2H9E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 24G Switch SVC
HV0W5E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 48G CL4 Switch SVC
HV1J3E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 48G Switch SVC
H83L4E	HPE Aruba Networking Foundational Care 5Y 4HR Exch Vol T2 6100 48G+ 740W SVC
HV2P3E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 12G CL4 Switch SVC
HV1P7E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 24G CL4 Switch SVC
HV2B5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 24G Switch SVC
HV0Q1E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 48G CL4 Switch SVC
HV1B9E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 48G Switch SVC
H83D8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite 6100 48G+ 740W SVC
HV2P4E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 12G CL4 Switch SVC
HV1P8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 24G CL4 Switch SVC
HV2B6E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 24G Switch SVC
HV0Q2E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 48G CL4 Switch SVC
HV1C0E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite CDMR 6100 48G Switch SVC
HY2S4E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 12G CL4 SVC
HY2P8E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 24G CL4 SVC
HY2R1E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 24G SVC
HY2M2E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 48G CL4 SVC
HY2N5E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 48G SVC
H83D7E	HPE Aruba Networking Foundational Care 5Y 4HR Onsite Hardware Only 6100 48G+ 740W SVC
H83D9E	HPE Aruba Networking Foundational Care 5Y 24x7 CDMR 6100 48G+ 740W SVC
HV2P6E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 12G CL4 Switch SVC
HV1Q0E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 24G CL4 Switch SVC

HV2B8E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 24G Switch SVC
HV0Q4E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 48G CL4 Switch SVC
HV1C2E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour 6100 48G Switch SVC
HV2P7E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 12G CL4 Switch SVC
HV1Q1E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 24G CL4 Switch SVC
HV2B9E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 24G Switch SVC
HV0Q5E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 48G CL4 Switch SVC
HV1C3E	HPE Aruba Networking Foundational Care 5Y CTR 6-Hour CDMR 6100 48G Switch SVC
H83E1E	HPE Aruba Networking Foundational Care 5Y CTR 6100 48G+ 740W SVC
H83E2E	HPE Aruba Networking Foundational Care 5Y CTR CDMR 6100 48G+ 740W SVC
H83D3E	HPE Aruba Networking Foundational Care 5Y NBD 6100 48G+ 740W SVC
H83D4E	HPE Aruba Networking Foundational Care 5Y NBD CDMR 6100 48G+ 740W SVC
HV2N8E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 12G CL4 Switch SVC
HV1P2E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 24G CL4 Switch SVC
HV2B0E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 24G Switch SVC
HV0P6E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 48G CL4 Switch SVC
HV1B4E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 48G Switch SVC
H83D1E	HPE Aruba Networking Foundational Care 5Y NBD Exch 6100 48G+ 740W SVC
HY2S2E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 12G CL4 SVC
HY2P6E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 24G CL4 SVC
HY2Q9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 24G SVC
HY2M0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 48G CL4 SVC
HY2N3E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 48G SVC
H83D0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Hardware Only 6100 48G+ 740W SVC
HV2V2E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 12G CL4 Switch SVC
HV1V6E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 24G CL4 Switch SVC
HV2H4E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 24G Switch SVC
HV0W0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 48G CL4 Switch SVC
HV1H8E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 48G Switch SVC
H83K9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T1 6100 48G+ 740W SVC
HV2V3E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 12G CL4 Switch SVC
HV1V7E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 24G CL4 Switch SVC
HV2H5E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 24G Switch SVC
HV0W1E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 48G CL4 Switch SVC
HV1H9E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 48G Switch SVC
H83L0E	HPE Aruba Networking Foundational Care 5Y NBD Exch Vol T2 6100 48G+ 740W SVC

HV2P0E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 12G CL4 Switch SVC
HV1P4E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 24G CL4 Switch SVC
HV2B2E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 24G Switch SVC
HV0P8E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 48G CL4 Switch SVC
HV1B6E	HPE Aruba Networking Foundational Care 5Y NBD Onsite 6100 48G Switch SVC
HV2P1E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 12G CL4 Switch SVC
HV1P5E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 24G CL4 Switch SVC
HV2B3E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 24G Switch SVC
HV0P9E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 48G CL4 Switch SVC
HV1B7E	HPE Aruba Networking Foundational Care 5Y NBD Onsite CDMR 6100 48G Switch SVC

HPE Aruba Networking Services

HPE Aruba Networking services simplify and accelerate the network technology lifecycle, enabling your network to scale with better predictability and cost-effectiveness. Whether you operate your own network and need to improve your IT efficiencies, or you want to offload some of the burden, we have the services you need to reach your goals.

Learn more about what HPE Services - Aruba Networking has to offer at: hpe.com/edge/services

Support Services

Our support portfolio provides the essential support elements as well as proactive and preventive features to help you improve your team's productivity and get the most from your network. Our support customers benefit from faster issue resolution, simplified operations and efficiencies, and reduced network issues.

Professional Services

With deep intellectual capital and purpose-built tools, our team delivers a range of standard and custom professional services designed to accelerate your value from HPE Aruba Networking technology.

Project based services include:

— Planning, audit, and assessment
— Architecture review and design
— Deployment, migration, and knowledge transfer

Annual subscription services include:

— Network optimization
— Intelligent Operations
— Customer Experience Management

Our Education Services allow your team to come up to speed quickly.

GreenLake for Networking

Deliver innovative business outcomes by leveraging new ways to consume, deploy and manage networks.

For additional technical information, available models and options, please reference the QuickSpecs

Visit HPE.com

Chat now

© Copyright 2026 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Parts and Materials: HPE will provide HPE-supported replacement parts and materials required to maintain the covered hardware.

Parts and components that have reached their maximum supported lifetime and/or the maximum usage limitations as set forth in the manufacturer's operating manual, product quick-specs, or the technical product data sheet will not be provided, repaired, or replaced as part of these services.

Arm and Arm Cortex are registered trademarks of Arm Limited.
sFlow is a registered trademark of InMon Corp.
All third-party marks are property of their respective owners.

Image may differ from the actual product.

PSN1013114991NZEN, September, 2026.

HEWLETT PACKARD ENTERPRISE

hpe.com